Uncontrolled when printed

Supersedes GERT8000-HB13 Iss 2 with effect from 03/09/2022 and comes into force on 03/12/2022



GERT8000-HB13 Rule Book Handbook 13

Duties of the person in charge of the siding possession (PICOS)

### Issue 3



September 2022 Comes into force 03 December 2022 Uncontrolled when printed Supersedes GERT8000-HB13 Iss 2 with effect from 03/09/2022 and comes into force on 03/12/2022

Published by: RSSB The authoritative version of this document is available at www.rssb.co.uk

**Contents approved by Traffic Operation and Management Standards Committee.** 

For information regarding the Rule Book, contact: https://customer-portal.rssb.co.uk

First issued June 2011 Issue 3, September 2022 Comes into force 03 December 2022

<sup>©</sup> Copyright 2022 Rail Safety and Standards Board Limited

Uncontrolled when printed Supersedes GERT8000-HB13 Iss 2 with effect from 03/09/2022 and comes into force on 03/12/2022

		Page
1	Definitions	2
2	General	2
3	Competence	3
4	Agreeing the arrangements	4
5	Protecting the possession	5
6	Siding next to a running line under possession	7
7	Allowing work to start	8
8	Change of PICOS	9
9	Giving up the possession	9

Supersedes GERT8000-HB13 Iss 2 with effect from 03/09/2022 and comes into force on 03/12/2022

# 1 Definitions

#### **Designated person**

A designated person (DP) is responsible for setting up protection so that people carrying out work related to maintaining and repairing rail vehicles will be protected from train movements.

#### **Engineering train**

This includes on-track machines but does not include on-track plant (OTP).

#### **On-track plant (OTP)**

Also known as 'in possession only rail vehicles' and includes road-rail vehicles (RRV), rail-mounted maintenance machines (RMMM) and RRV/RMMM trailers and attachments with guidance wheels.

#### Train

This includes a light locomotive, self-propelled rail vehicle, on-track machine, an RRV in rail mode and an RMMM.

## 2 General

Before allowing engineering work or on-tracking of OTP to take place in a siding or group of sidings, you will be appointed to take possession of the sidings concerned as shown in this handbook.

Wherever possible you should arrange to take possession of the whole of each affected siding.

If a possession of a siding will be taken in association with a possession of an adjacent running line, you may, if competent, also be the person in charge of the possession (PICOP) of that possession or the engineering supervisor (ES) or safe work leader (SWL) of an adjacent work site.

If you are an IWA, you must not arrange a possession in sidings for the protection of anyone except yourself.

Local instructions may be published by Network Rail in the *Sectional Appendix* or by the operator of a depot. Those local instructions may modify the arrangements shown in this handbook. You must be aware of and apply these instructions where necessary.

## 3 Competence

To act as a person in charge of a siding possession (PICOS), you must have been passed as competent in the rules shown in this handbook and have with you a valid certificate of competence issued by your employer for either a COSS, IWA or SWL.

# 4 Agreeing the arrangements

#### 4.1 Agreement with the person responsible

You must agree the following details with the person who is responsible for the operation of the siding.

- Your name and contact details.
- The location of the siding or sidings involved.
- Whether you will take possession of the whole length of a siding or just part of it.
- Whether you will need to take possession of more than one siding.
- How you will arrange line protection.
- The date and time you will take possession and by when it will be given up.

#### 4.2 Telling the shunter

If involved, you must make sure the shunter is told about the possession arrangements. You do not need to do this yourself if the person responsible for the operation of the siding tells you that they will.

#### **4.3 Recording the arrangements**

You must record in writing on the document provided by your employer:

- which siding is affected
- the siding-protection arrangements
- the date and time the possession is taken.

Supersedes GERT8000-HB13 Iss 2 with effect from 03/09/2022 and comes into force on 03/12/2022

# **5** Protecting the possession

# 5.1 Possession of the whole length of a siding

Before you allow any work to start or OTP to be placed on the track in the siding, you must arrange the line protection as follows.

- Make sure the points leading to the siding are set to prevent movements from entering the siding.
- Clip and padlock the points.
- Keep the key to the padlock until the possession is given up.

#### 5.2 Possession of part of one siding

If it is not possible to block the whole of the siding, you must make sure that no movement approaches the affected part of the siding by placing line protection in the siding concerned.

The line protection is:

- a sleeper secured across the rails, and
- a possession limit board (PLB), red flag or red light placed at the sleeper so that it may clearly be seen by an approaching movement.

# **5.3** Points worked from a signal box or ground frame

If the points leading to the siding are worked from a signal box or ground frame, you must not clip the points. However, you must get confirmation from the signaller or ground frame operator that the points will be kept in the position to prevent movements from entering the siding.

#### 5.4 If movements can enter from either end

If movements can enter the siding from either end, you must arrange line protection at both ends.

# 5.5 If work is to be carried out on a rail vehicle

If work is to be carried out on a rail vehicle standing within the possession, the DP will ask you to stop any movements towards that vehicle.

If the DP asks you to stop movements on an adjacent running line you must ask:

- the PICOP, if that line is under possession
- the signaller, if the line is not under possession.

If the DP asks you to stop movements on an adjacent siding you must ask:

- the PICOS, if that siding is under possession
- the person in charge or the signaller, if that siding is not under possession.

If work is to take place on an item of on-track plant (OTP) on any line, the machine controller (MC) will ask you.

When movements have been stopped on any line concerned, you must tell the person who asked you.

You must not allow any movements on the line affected, or tell the signaller that the line blockage can be given up, until the person who asked you to arrange protection tells you that:

- work on the vehicle has been completed or suspended
- protection is no longer required.

# 6 Siding next to a running line under possession

#### 6.1 Line protection arrangements

If the possession of the siding is taken in association with a possession of an adjacent running line, you do not need to provide line protection to the siding as shown in section 5 unless one of the following applies.

- The siding is a through siding and you need to prevent access at the far end of the siding.
- The possession of the siding will be taken before the adjacent running line possession.

When possession of the siding will be kept after the adjacent running line possession is given up, you must make sure line protection is provided before the adjacent running line possession is given up.

# 6.2 Movements to or from the running line under possession

If the siding is to be used to allow movements to enter or leave an adjacent possession, you must agree with the PICOP, ES or SWL, as appropriate, and the signaller or ground frame operator, if involved, how this will be done.

You must make suitable arrangements for the safety of your group and any other group or individual who is working under the protection of your possession while movements take place.

If points have been secured to protect the possession, you must make sure the points are again secured once the movement has been completed.

# 7 Allowing work to start

When you have completed the arrangements for taking possession of the siding, you may allow your group, or another group or individual, to start work in the siding, or allow OTP to be on-tracked.

You must record the name and contact number of any other COSS, DP, IWA or SWL to whom you give permission to share your protection.

You must brief anyone who is permitted to share your protection about the limits and any known hazards.

This section 7 does not apply to an IWA.

# 8 Change of PICOS

When going off duty, you must give the new PICOS the details about:

- the limits of your possession
- the line-protection arrangements
- any movement that you have authorised which has not been completed
- any other groups or individuals working under your protection.

If you are the new PICOS, you must tell the signaller, if involved.

## 9 Giving up the possession

#### 9.1 Work suspended or completed

Before you make arrangements to give up the possession, you must make sure that:

- the siding is safe for movements
- each COSS, DP, IWA or SWL you have allowed to share your protection has assured you that your protection arrangements are no longer needed
- any OTP have been removed from the siding.

You must then remove any line protection you placed in the siding.

#### 9.2 Telling others

You must tell the following that you have removed the line protection and the possession has been given up.

- The signaller or ground frame operator, if involved.
- The person who is responsible for the operation of the siding.
- The shunter. You do not need to do this yourself if the person responsible for the operation of the siding or the signaller tells you that they will.

#### 9.3 Recording the arrangements

You must record in writing:

- the date and time at which each COSS, DP, IWA or SWL confirms to you that they no longer need to share your protection
- the date and time the possession is given up.

Uncontrolled when printed Supersedes GERT8000-HB13 Iss 2 with effect from 03/09/2022 and comes into force on 03/12/2022

Uncontrolled when printed Supersedes GERT8000-HB13 Iss 2 with effect from 03/09/2022 and comes into force on 03/12/2022



Uncontrolled when printed Supersedes GERT8000-HB13 Iss 2 with effect from 03/09/2022 and comes into force on 03/12/2022

Uncontrolled when printed

Supersedes GERT8000-HB13 Iss 2 with effect from 03/09/2022 and comes into force on 03/12/2022

Corporate member of Plain English Campaign			
Committed to clearer			
172	25		



Contact https://customerportal.rssb.co.uk Tel +44 (0) 20 3142 5300 Twitter @RSSB\_rail Web www.rssb.co.uk

Rail Safety and Standards Board Limited The Helicon One South Place London EC2M 2BB